

12 V Pure sine wave car DC-AC power inverter, 1000 W

EG-PWC-PS1000-01

PURE SINE POWER

- A 230V power source in your car
- Pure sine wave: more efficiency than before
- Practical USB port for charging mobile devices



Особенности

- Single socket 1000 W car power inverter with pure sine wave output
- Allows to connect any AC powered electronics (max. 1000 Watt), like notebooks, HiFi or video equipment, chargers of mobile phones/ cameras, electrical tools etc.
- Integrated overload-, short-circuit and reverse polarity protection, plus a built-in cooling fan provide a stable power supply
- LED status indicator and alarm buzzer

Упаковка

Кол-во в коробке, шт	4
Объем коробки, куб.м.	0.05544
Вес коробки, кг	13.46
Размеры индивидуальной упаковки ДхШхВ:	425x140x200 mm
Размеры картонной коробки ДхШхВ:	440x420x300 mm
Страна происхождения	CN
Баркод	8716309124065
Таможенный код	8504408790

Содержимое упаковки

Car power inverter
Ring terminal power cables
User manual

Сертификаты



Спецификация

Input: 10-16 VDC (accumulator directly)
Output: 230 VAC +/-10% at 50 Hz (+/-1Hz), pure sine wave, THD < 3%, 90% efficiency
Power output: 1000 W continuous power (peak power 2000 W)

Internal output overcurrent protection: 5.7 A
USB power output: 5 V / 2.1 A
Recommended operating temperature: +0...+40 °C at 100% load; up to 60 °C at 50% load
Material: aluminum and plastic
Cable: 80 cm (10 sq.mm) ring terminals, 100A terminal
Dimensions: 310 x 150 x 70 mm
Net weight: 2.71 kg

Системные требования

Safety precautions:
Connect the inverter to car's accumulator directly, being careful with the polarity